



## ARGO-1500-EM

CLEVERTRONICS Argo 1500mm Weatherproof Emergency Batten, Switchable Colour



### PRODUCT INFORMATION

<b>Product Code</b>	ARGO-1500-EM
<b>MIC</b>	AUB03520140001
<b>Description</b>	Argo 1500mm Weatherproof Emergency Batten, Switchable Colour
<b>Colour CCT</b>	Switchable 3000K / 4000K (Default) / 5700K
<b>Output Configuration</b>	Fixed Single Output
<b>Battery Configuration</b>	Integral Battery
<b>Construction</b>	Polycarbonate Base, Polycarbonate Diffuser and Captive Stainless-Steel Clips (SS301)
<b>Diffuser</b>	Polycarbonate
<b>Mounting</b>	Surface Mount
<b>Operating Mode</b>	Sustained
<b>Testing System</b>	N/A
<b>Battery</b>	Lithium Iron Phosphate, 3.2V 3200mAh
<b>Charging Method</b>	Intelligent Current Limited Constant Voltage
<b>Sensor Capability</b>	N/A
<b>Dimensions LxWxH (mm)</b>	1565x121x88
<b>Weight (kg)</b>	3.1
<b>Driver / Ballast</b>	LED Driver - Xitanium, 72w, 1.2-1.4A, 51V DS 230V
<b>Lamp(s)*</b>	LED strip module, 3000K / 5700K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 168,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 84,000hr L90/B10 Ta 40°C; LM80 Report 37,000hr, Projected 37,000hr
<b>Supply Voltage</b>	220-240V~ 50Hz
<b>Power Factor</b>	0.95 @ Default
<b>Supply Current</b>	245mA +/- 20mA
<b>Inrush Current (Max)</b>	35A<202μs
<b>Earth Leakage</b>	0.167mA
<b>Total lumen output</b>	6244lm (115.72lm/W) @ default (refer to next page for details)
<b>Power Consumption</b>	53.6W @ default (refer to next page for details)
<b>Operating Temperature</b>	0°C to 40°C
<b>IP Rating</b>	IP65
<b>Impact Rating</b>	IK08
<b>LED MacAdam Step (SDCM)</b>	5
<b>AS2293 Classification</b>	C0=D50 C90=D32
<b>Applicable Standards</b>	AS/NZS3820, CISPR15, AS/NZS2293.3
<b>Compliance Marking</b>	



## ARGO-1500-EM

CLEVERTRONICS Argo 1500mm Weatherproof Emergency Batten, Switchable Colour



### REPLACEMENT PARTS

PART NUMBER	DESCRIPTION
1330108	240V Driver
8002851	240V LED Panel
AUM03570030001 ELIFE-X-LI-CKIT-2LED-SL-NP-400	Emergency Driver Pack
8002700	Emergency LED Panel
1560050	Battery
N/A	Microwave Motion Sensor

Power Consumption & Lumen Output	Output (1200mA)				
	Max Charge, Lamp On	Standby Charge, Lamp On	Standby Charge, Lamp Min. 10% (sensor version only)	Standby Charge, Lamp Off	Lumen Output
3000K	57.4W	56.5W	N/A	0.4W	5904lm
4000K (DEFAULT)	54.0W	53.6W	N/A	0.4W	6244lm
5700K	57.4W	56.5W	N/A	0.4W	5631lm

\*The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications, or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order