

LCFLED-HV CLEVERTRONICS L10 CLEVERFIT LED EXIT





| PRODUCT INFORMATION | |
|--------------------------|---|
| Part Number | LCFLED-HV |
| MIC | AUA01810010002 |
| Description | L10 Optimum Cleverfit Emergency Exit |
| Construction | ABS body and diffuser with polycarbonate clear tamper proof cover |
| Mounting | Wall, ceiling single-sided & ceiling double-sided |
| Dimensions L x W x H | 355mm x 80mm x 215mm |
| Weight | 1.6kg |
| Operating Mode | Maintained |
| Testing System | Zoneworks XT HIVE (RF) |
| Battery | Lithium Nanophosphate, 3.3V 2500mAh |
| Charging Method | Intelligent current limited constant voltage |
| Diffuser | All directional inserts included in the box |
| Lamp(s) | 6 x LED, Lifetime: >100,000hrs (AS/NZS2293.3 LSL=12Y/00M) |
| Operating Voltage | 240V AC; 50Hz |
| Power Consumption | 2.8 Watts (Standby) 4.0 Watts (Max) |
| IP Rating | IP20 |
| Operating Temperature | 1°C to 40°C |
| AS2293 Classification | C0=D6.3 C90=D5 |
| Viewing Distance | 24m |
| Applicable Standards | AS/NZS3820, CISPR15, AS/NZS2293.3 |
| Compliance Marking (RCM) | <u>&</u> |

| REPLACEMENT PARTS | |
|-------------------|--|
| PART NUMBER | DESCRIPTION |
| 1530090 | BATT:L10 3.3V 2.5AH 390mm lead, no BRKT |
| 8002710 | LED: PCA: Duris LED Strip Cleverfit Pro CT10276-D3 |
| 8002358 | EM DRIVER: PCA: CT10164-L6 6C43-83 DALIREG, HV |
| 8003191 | PCA: RF Node CT10678-A12 Int Antenna LLPro |

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order.

