



ARGOPRO-600

CLEVERTRONICS Argonaut Pro 600mm Weatherproof Batten



PRODUCT INFORMATION	
Product Code	ARGOPRO-600
MIC	INB04620160001
Description	Argonaut Pro 600mm Weatherproof Batten
Colour CCT	4000K
Output Configuration	Fixed Single Output
Construction	Polycarbonate Base and Diffuser w/Stainless Steel Clips (SS316)
Diffuser	Polycarbonate
Mounting	Surface Mount
Sensor Capability	n/a
Dimensions LxWxH (mm)	655x160x105
Weight (kg)	1.4
Driver / Ballast	LED Driver - 40W, 500-1050mA, 15-50V
Lamp(s)*	LED strip module, 4000K, Ra>80 L70/B50 Ta 40°C; LM80 Report >60,000hr, Projected 184,000hr L80/B20 Ta 40°C; LM80 Report >60,000hr, Projected 100,000hr L90/B10 Ta 40°C; LM80 Report 43,000hr, Projected 43,000hr
Supply Voltage	220-240V~ 50Hz
Power Factor	0.91 @ default
Supply Current	88mA +/-20mA
Inrush Current (Max)	15A<250μs
Earth Leakage	0.027mA
Total Lumen Output	2564 lm (140 lm/W) @ default (refer to next page for details)
Power Consumption	18.3W @ default (refer to next page for details)
Operating Temperature	-25°C to 40°C
IP Rating	IP65
Impact Rating	IK08
LED MacAdam Step (SDCM)	3
Applicable Standards	AS/NZS3820, CISPR15, AS/NZS60598.1, EN 60598-2-1, BS EN IEC 55015,BS EN 61547, BS EN IEC 61000-3-2
Compliance Marking	



ARGOPRO-600

CLEVERTRONICS Argonaut Pro 600mm Weatherproof Batten



REPLACEMENT PARTS

COMPONENT	PART NUMBER & DESCRIPTION
240V Driver	1330029 - LED Driver - 40W, 500-1050mA, 15-50V
240V LED Strip	8002754 - PCA: LED Strip ARGOPRO-600,HT10515-A1,16P8S, 4000K
Sensor	n/a

Power Consumption & Lumen Output	Lamp On	Lamp Min. 10% (sensor version only)	Lumen Output
Output (700mA)	18.3W	n/a	2564 lm

*The projected value has been calculated by extrapolation of the LM80 data using the Energy Star Calculator

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order