

ARGOSQ-DDCLEVERTRONICS ARGONAUT SQUARE WEATHERPROOF LUMINAIRE



PRODUCT INFORMATION	I	
Part Number	ARGOSQ-DD	
MIC	AUS04320060001	
Description	Argonaut Square Weatherproof Luminaire with DALI Driver	
Output Configuration	Configurable Dual Output	
Construction	Die-cast Aluminium Body with Polycarbonate Diffuser	
Mounting	Surface mount	
Dimensions L x W x H	321mm x 321mm x 97mm	
Weight	3.0kg	
Diffuser	Polycarbonate	
Driver / Ballast	LED Driver-LCA 25W 350-1050mAone4all SC PRE,20-50V	
Lamp(s)	LED module, 4000K cool white, Ra>80 L70/B50 Ta 40°C; Reported >60,000hr, Projected 205,000hr L80/B20 Ta 40°C; Reported >60,000hr, Projected 100,000hr L90/B10 Ta 40°C; Reported >43,000hr, Projected 43,000hr	
Supply Voltage	220-240V~ 50Hz	
Power Factor	0.91	
Supply Current	100mA +/- 20mA	
Inrush Current (max)	30.8A<100μs	
Earth Leakage	0.35mA	
Total Lumen Output	3242lm @ 152.9/W @ default (refer to next page for details)	
Power Consumption	21.2W @ default (refer to next page for details)	
IP Rating	IP65	
IK Rating	IK10	
Operating Temperature	0°C to 40°C	
AS2293 Classification	N/A	
Applicable Standards ANZ	AS/NZS3820, AS/NZS2293.3, CISPR15	
Compliance Marking (RCM)		

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order.





ARGOSQ-DDCLEVERTRONICS ARGONAUT SQUARE WEATHERPROOF LUMINAIRE

REPLACEMENT PARTS		
PART NUMBER	DESCRIPTION	
8050780	LED Panel	
1330038	240V Driver	

Power Consumption & Lumen Output	Power Consumption Lamp On	Lumen Output
(470mA) DEFAULT	21.2W	3242lm

The product details described in this document are current as at the version date of the document. We reserve the right to change product design, specifications or materials (Specifications) as part of our continuous improvement program. Please confirm the applicable Specifications at the time of placing your order.

